





Code: **ICF**

Socket Cap Screw Counterbore




Application Examples



M	d	d1	d2	l	l1	l2
M3	6	3.2	5	71	14	4
M4	8	4.3				
M5	10	5.3	8	80	18	6
M6	11	6.4				
M8	15	8.4	12.5	100	22	8
M10	18	10.5				10
M12	20	13				12
M14	24	15				14
M16	26	17				16
M18	30	19				18
M20	33	20				20

Order: **ICF. M x d**


Straight Stud



Order	M	Steel	INOX
GSM.3	M3	✓	
GSM.4	M4	✓	
GSM.5	M5	✓	
GSM.6	M6	✓	✓
GSM.8	M8	✓	✓
GSM.10	M10	✓	✓
GSM.12	M12	✓	✓
GSM.14	M14	✓	✓
GSM.16	M16	✓	✓
GSM.18	M18	✓	
GSM.20	M20	✓	
GSM.22	M22	✓	
GSM.24	M24	✓	

Page


128



Order / Code: **HIC. d x L**

Countersunk Head Screw

Class: 10.9 DIN 7991




Code: **HIC**

d (M)	l _{mm}	l ₁	D	k	s
M3 x 05	8	3.2	6	1.7	2
	10				
	15				
M4 x 07	10	4.4	8	2.3	2.5
	15				
	20				
	25				
M5 x 08	30	5.2	10	2.8	3
	10				
	15				
	20				
	25				
	30				
	35				
M6 x 1	40	6.3	12	3.3	4
	10				
	15				
	20				
	25				
	30				
	35				
M8 x 1.25	40	8.2	16	4.4	5
	10				
	15				
	20				
	25				
	30				
	35				
M10 x 1.50	40	10	20	5.5	6
	50				
	15				
	20				
	25				
	30				
	35				
M12 x 1.75	40	11.8	24	6.5	8
	50				
	60				
	20				
	25				
	30				
	35				
M16 x 2	40	15.4	30	8.5	10
	50				
	60				
	70				
	25				
	30				
	35				



Order / Code: **SEC. d x L**

Hex-socket Set Screws



Code: **SEC**


d	l _{mm}	Z	SW
M3 x 05	8	0.5	1.5
	10		
	15		
M4 x 07	8	0.7	2
	10		
	15		
	20		
M5 x 08	10	0.75	2.5
	15		
	20		
	25		
M6 x 1	30	1.0	3.0
	10		
	15		
	20		
	25		
	30		
	35		
M8 x 1.25	40	1.2	4.0
	10		
	15		
	20		
	25		
	30		
	35		
M10 x 1.50	45	1.5	5.0
	50		
	10		
	15		
	20		
	25		
	30		
M12 x 1.75	35	2.0	6.0
	40		
	45		
	50		
	55		
	60		
	20		
M14 x 2	25	2	7
	30		
	35		
	40		
	50		
	60		
	20		
M16 x 2	25	2	8
	30		
	35		
	40		
	50		
	60		
	20		



Order / Code: **DKM. d1 x L**

Low Head Socket Cap Screw

Class: 8.8 DIN 79849



Code: **DKM**

d1 (M)	l _{mm}	b	d2	k	s
M4	10	8	7	2.8	2.5
	12	10			
	16	14			
	20	14			
M5	25	14	8,5	3,5	3
	10	8			
	12	10			
	16	14			
	20	16			
	25	16			
	30	16			
M6	35	16	10	4	4
	40	16			
	50	16			
	10	8			
	12	10			
	16	14			
	20	18			
M8	25	18	13	5	5
	30	18			
	35	18			
	40	18			
	50	18			
	16	14			
	20	18			
M10	25	22	16	6	7
	30	22			
	35	22			
	40	22			
	50	22			
	60	22			
	16	14			
M12	20	18	18	7	8
	25	23			
	30	28			
	35	30			
	40	30			
	50	30			
	60	30			